Installation relay, 230 V AC, 1NO, 16A

Part no. Z-R230/16-10 Catalog No. ICS-R16A230B100

**EL-Nummer** 

4100208

(Norway)

## Design verification as per IEC/EN 61439

| Technical data for design verification   |                  |   |  |
|--|------------------|---|--|
| Rated operational current for specified heat dissipation   | In               | Α | 16   |
| Equipment heat dissipation, current-dependent  | P <sub>vid</sub> | W | 1.6  |
| IEC/EN 61439 design verification   |                  |   |  |
| 10.2 Strength of materials and parts   |                  |   |  |
| 10.2.2 Corrosion resistance  |                  |   | Meets the product standard's requirements.   |
| 10.2.3.1 Verification of thermal stability of enclosures   |                  |   | Meets the product standard's requirements.   |
| 10.2.3.2 Verification of resistance of insulating materials to normal heat   |                  |   | Meets the product standard's requirements.   |
| 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects |                  |   | Meets the product standard's requirements.   |
| 10.2.4 Resistance to ultra-violet (UV) radiation   |                  |   | Meets the product standard's requirements.   |
| 10.2.5 Lifting   |                  |   | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.2.6 Mechanical impact   |                  |   | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.2.7 Inscriptions  |                  |   | Meets the product standard's requirements.   |
| 10.3 Degree of protection of ASSEMBLIES  |                  |   | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.4 Clearances and creepage distances   |                  |   | Meets the product standard's requirements.   |
| 10.5 Protection against electric shock   |                  |   | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.6 Incorporation of switching devices and components   |                  |   | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.7 Internal electrical circuits and connections  |                  |   | Is the panel builder's responsibility.   |
| 10.8 Connections for external conductors   |                  |   | Is the panel builder's responsibility.   |
| 10.9 Insulation properties   |                  |   |  |
| 10.9.2 Power-frequency electric strength   |                  |   | Is the panel builder's responsibility.   |
| 10.9.3 Impulse withstand voltage   |                  |   | Is the panel builder's responsibility.   |
| 10.9.4 Testing of enclosures made of insulating material   |                  |   | Is the panel builder's responsibility.   |
| 10.10 Temperature rise   |                  |   | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| 10.11 Short-circuit rating   |                  |   | Is the panel builder's responsibility. The specifications for the switch<br>gear must be observed. $\label{eq:constraint}$       |
| 10.12 Electromagnetic compatibility  |                  |   | Is the panel builder's responsibility. The specifications for the switch<br>gear must be observed. $\label{eq:constraint}$       |
| 10.13 Mechanical function  |                  |   | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.                         |
|  |                  |   |  |

## **Technical data ETIM 7.0**

Devices for distribution board-/surface mounting (EG000062) / Installation relay (EC001652)

Electric engineering, automation, process control engineering / Electrical installation, device / Modular serial built-in device for electrical circuit distributors / Installation relay for distribution board (ecl@ss10.0.1-27-14-23-09 [AFZ821014])

| DUBIT (ECIESSITU.1-27-14-25-05 [AFZ021014])   |    |            |  |  |  |
|---|----|------------|--|--|--|
| Function                                      |    | Mechanical |  |  |  |
| Mounting method                               |    | DIN rail   |  |  |  |
| Width in number of modular spacings           |    | 1          |  |  |  |
| Built-in depth                                | mr | n 60       |  |  |  |
| Number of contacts as normally open contact   |    | 1          |  |  |  |
| Number of contacts as normally closed contact |    | 0          |  |  |  |
| Number of contacts as change-over contact     |    | 0          |  |  |  |
| Control voltage 1                             | V  | 196 - 250  |  |  |  |
| Type of control voltage 1                     |    | AC         |  |  |  |
| Frequency control voltage 1                   | Hz | 50 - 60    |  |  |  |
| Control voltage 2                             | V  | 0 - 0      |  |  |  |

| Type of control voltage 2                         |    | AC        |
|---|----|-----------|
| Frequency control voltage 2                       | Hz | 0 - 0     |
| Rated current                                     | А  | 16        |
| Supply voltage                                    | V  | 240 - 240 |
| Voltage type of supply voltage                    |    | AC        |
| Max. incandescent lamp load                       | W  | 720       |
| Max. load fluorescent lamp                        | VA | 303       |
| Max. load fluorescent lamp (Duo circuit)          | VA | 541       |
| Max. load fluorescent lamp (parallel compensated) | VA | 271       |
| Max. switching current (cos phi = 0.6)            | А  | 5         |